7. Electrical Parts List

7-1 CS15A8WT7X/SAP

Loc. No.	Code No.	Description ; Specification	Remark

ASSY PCB MAIN(OPT)

* AA94-02621CASSY PCB MAIN(OPT);CS15A8WT7X/SAP,KS2A,S

C102	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
C103	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C104	2401-000142	C-AL;1000uF,20%,16V,WT,TP,10x20,5	
C105	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C106	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C115	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C116	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C201	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
C202	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C203	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C206	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C211	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C212	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
C213	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
C214	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C215	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C216	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C217	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
C218	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C219	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C220	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C221	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C222	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C223	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C224	2201-002031	C-CERAMIC,DISC;0.005nF,0.5pF,50V,NP0,TP,	
C225	2201-002031	C-CERAMIC,DISC;0.005nF,0.5pF,50V,NP0,TP,	
C226	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C228	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
C229	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C231	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C232	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C233	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
C234	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
C235	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
C236	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
C237	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
C239	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C242	2301-000310	C-FILM,PEF;68nF,5%,50V,TP,8.0X8.5X4.0X5,	
C243	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C244	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C245	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C247	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C301	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C302	2401-000326	C-AL;100uF,20%,35V,GP,TP,8x11.5,5	
C303	2201-002031	C-CERAMIC,DISC;0.005nF,0.5pF,50V,NP0,TP,	
C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
C305	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
C306	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C308	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C401	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
C403	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
C404	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
C407	2301-001338	C-FILM,MPE-PPF;0.68nF,5%,1.6kV,TP,28x7x1	
C408	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
C412	2305-000178	C-FILM,MPEF;10nF,5%,100V,TP,-,5mm	
C414	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
C420	2301-001065	C-FILM,MPPF;47nF,5%,630V,TP,19x15.5x7,7.	
C421	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
C422	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
C425	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C427	2401-002267	C-AL;2.2uF,20%,250V,GP,TP,8x11.5,5	
C501	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.	
C502	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.	
C503	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.	
C504	2305-000704	C-FILM,MPEF;100nF,5%,250V,TP,16.5x10.3x5	
C505	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C506	2305-000704	C-FILM,MPEF;100nF,5%,250V,TP,16.5x10.3x5	
C507	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C508	2305-000704	C-FILM,MPEF;100nF,5%,250V,TP,16.5x10.3x5	
C509	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C511	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
C512	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
C513	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
C514	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
C515	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
C516	2201-002063	C-CERAMIC,DISC;10nF,+80-20%,3KV,Y5V,TP,1	
C605	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
C607	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C608	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C609	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C610	2301-000111	C-FILM,PEF;1.8nF,5%,50V,TP,6.5x3.0x5.5mm	
C611	2301-000111	C-FILM,PEF;1.8nF,5%,50V,TP,6.5x3.0x5.5mm	
C612	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
C613	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
C617	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
C620	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C621	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
C622	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C623	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C624	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C625	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C626	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C627	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C628	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C629	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C630	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C631	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C632	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C634	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C635	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C636	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
C637	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C638	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C639	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C640	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C641	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C642	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C643	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C644	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C645	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C646	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C647	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
C648	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C650	2201-000558	C-CERAMIC,DISC;0.47nF,10%,50V,Y5P,TP,5x3	
C652	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C654	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
C656	2201-000304	C-CERAMIC,DISC;0.001nF,0.25pF,50V,NP0,TP	
C657	2201-000304	C-CERAMIC,DISC;0.001nF,0.25pF,50V,NP0,TP	
C660	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C701	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C707	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
C708	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
C803	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
C804	2201-000332	C-CERAMIC,DISC;2.2nF,20%,250V,Y5U,TP,9x4	
C805	2201-000332	C-CERAMIC,DISC;2.2nF,20%,250V,Y5U,TP,9x4	
C806	2401-003025	C-AL;330uF,20%,400V,GP,ST,30x40,10	
C807	2301-001342	C-FILM,PPF;1.5nF,5%,800V,TP,15x6.5x11.5m	

Loc. No.	Code No.	Description ; Specification	Remark
C808	2401-002300	C-AL;47uF,20%,50V,GP,TP,6.3x11,5	
C809	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
C811	2301-000310	C-FILM,PEF;68nF,5%,50V,TP,8.0X8.5X4.0X5,	
C814	2201-000991	C-CERAMIC,DISC;0.56nF,10%,2kV,Y5P,TP,7.5	
C815	2401-003026	C-AL;330uF,20%,200V,GP,ST,22x35,10	
C816	2401-000293	C-AL;100uF,+30-10%,200V,GP,TP,16x25	
C817	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C818	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
C819	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C820A	2401-001363	C-AL;470uF,20%,16V,GP,TP,10x12.5,5	
C821	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
C822	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C823	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C825	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C826	2401-001363	C-AL;470uF,20%,16V,GP,TP,10x12.5,5	
C827	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C829	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C831	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C832	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C838	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C839	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C840	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C841	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
C843	2201-000374	C-CERAMIC,DISC;0.22nF,5%,50V,NP0,TP,10.5	
C901	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C902	2401-000553	C-AL;1uF,10%,50V,GP,TP,5x11,5	
C904	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
C905	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C907	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C908	2202-000863	C-CERAMIC,MLC-AXIAL;560pF,10%,50V,Y5P,TP	
C910	2201-000980	C-CERAMIC,DISC;0.03nF,5%,50V,NP0,TP,5x3,	
C911	2201-000980	C-CERAMIC,DISC;0.03nF,5%,50V,NP0,TP,5x3,	
C913	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
C914	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C915	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
C916	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C917	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C918	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C919	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C920	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
C921	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
CG501	AA27-00084A	COIL;S-23,-,-,-,-,-,-,S-23,5000Mohm	
CG502	AA27-00084A	COIL;S-23,-,-,-,-,-,-,S-23,5000Mohm	
CG503	AA27-00084A	COIL;S-23,-,-,-,-,-,-,S-23,5000Mohm	
CN501B	AA39-20054A	LEAD CONNECTOR-ASSY;-,YBNH025-06,S,6P,40	
CN502B	AA39-20053A	LEAD CONNECTOR-ASSY;-,YBNH025-05,S,5P,40	
CN602	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
CN701	3711-002647	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
⚠ CR401S	2303-000013	C-FILM,PPF;2.7nF,5%,1.6KV,TP,28.5x13.5x6	
⚠ CR402S	2303-000013	C-FILM,PPF;2.7nF,5%,1.6KV,TP,28.5x13.5x6	
⚠ CR405S	2306-000166	C-FILM,MPPF;220nF,5%,400V,TP,26x17x9,20m	
⚠ CW901	2503-000156	C-NETWORK;100pFx4,20%,50V	
⚠ CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ CX802S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ CY802S	2201-000446	C-CERAMIC,DISC;3.3nF,20%,400V,Y5U,TP,15x	
D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D203	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D204	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D205	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D206	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D208	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D209	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D210	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D212	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
D402	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D406	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D407	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
D408	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
D411	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
D413	0402-000537	DIODE-RECTIFIER;RH1A,600V,0.6A,DO-204AC	
D502	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	

Loc. No.	Code No.	Description ; Specification	Remark
D602	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D801	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ D801S	0402-000549	DIODE-BRIDGE;RBV606,600V,6A,-,BK	
D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
D804	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D810	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D811	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D813	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
D816	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
D901	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D902	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D903	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D904	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D905	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D906	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D907	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D908	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
⚠ DDR01	0402-000231	DIODE-RECTIFIER;FMG-G26S,600V,4A,TO-220	H/SINK
⚠ DDR01	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	H/SINK
⚠ DDR01	1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	H/SINK
DH01	0502-001115	TR-POWER;KSC5386,NPN,50W,TO-3PF,ST,8-	
DZ201	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ202	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ203	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ204	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
DZ304	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
DZ305	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
DZ306	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
DZ402	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
DZ501	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
DZ502	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
DZ601	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ602	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ603	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ801	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
DZ802	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ803	0403-001167	DIODE-ZENER;MTZJ30D,30V,29.02-30.51V,500	
DZ804	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
DZ805	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
DZ806	0403-000714	DIODE-ZENER;MTZJ3.3B,3.3V,3.32-3.53V,500	
DZ808	0403-000719	DIODE-ZENER;MTZJ7.5B,7.5V,7.07-7.45V,500	
DZ901	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ902	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ904	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ905	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ906	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ907	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
⚠ FD801S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
⚠ FD802S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
⚠ FD803S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
⚠ FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
⚠ IC201S	1204-001632	IC-VIDEO PROCESS;VDP3108B-C3,DIP,64P,-,P	
⚠ IC301	1204-000517	IC-VERTIVAL DEF.;LA7845,SIP,7P,-,PLASTIC	H/SINK
⚠ IC501	1201-000539	IC-VIDEO AMP;6101,ZIP,9P,-,SINGLE,-,PLAS	
⚠ IC502	1201-000539	IC-VIDEO AMP;6101,ZIP,9P,-,SINGLE,-,PLAS	
⚠ IC503	1201-000539	IC-VIDEO AMP;6101,ZIP,9P,-,SINGLE,-,PLAS	
⚠ IC601	1204-001715	IC-SOUND PROCESSOR;MSP3400D-C5,DIP,52P,5	
⚠ IC602	1201-001308	IC-POWER AMP;7266,ZIP,15P,-,DUAL,26dB,PL	H/SINK
⚠ IC801S	1203-001494	IC-PWM CONTROLLER;3S0680RF,TO3PF-5L,5,21	H/SINK
⚠ IC803	1203-001697	IC-VOLTAGE REGULATOR;78R08,TO-220,4P,-,P	
⚠ IC804	1203-000284	IC-POSI.FIXED REG.;7806,TO-220,3P,-,PLAS	H/SINK
⚠ IC901	AA09-00041A	IC-MCU;SDA555X-OTP,SDA555X-OTP,-,-,52	
⚠ IC902	1103-001171	IC-EEPROM;24L161,16KBIT,DIP,8P,300MIL,10	
⚠ IC903	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
⚠ IC904	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	
J111	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
J239	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
J501	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
J625	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
J831	2701-000300	INDUCTOR-AXIAL;1.3UH,10%,2.5X3.4MM	
J835	2701-000300	INDUCTOR-AXIAL;1.3UH,10%,2.5X3.4MM	

Loc. No.	Code No.	Description ; Specification	Remark
J909	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JA701	3722-001333	JACK-RCA;9P,3.2mm,NI,BLK,-	
L102	2701-000200	INDUCTOR-AXIAL;5.6uH,10%,4.2x9.8mm	
L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
L201	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L203	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L204	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L209	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L302	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L303	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L407	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
L409	AA27-00013A	COIL-HORIZ.WIDTH;-,50UH,OS 6X20,-,BK	
L601	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
L602	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L603	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L604	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
L605	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L606	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L607	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L608	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L609	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
L610	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L705	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L706	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L801	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L804	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
L806	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L807	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
L808	AA27-10002L	COIL-CHOKE;-,24UH,K,-,2A,-,24UH-K,10X10M	
L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L901	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
L903	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
L904	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
L905	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L906	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
⚠ LC801S	AA27-00077A	COIL DEGAUSSING;-,-,4.3mH,20%,70T,9OHM,-	
LD901	AA96-30001B	ASSY-LED,GUIDE;-,AA61-50055A,DL-G5RGA,-	
⚠ LR401S	AA27-30003R	COIL-LINEARLITY;-,220uH,YL10x10,0.35mm,2	
⚠ LX801S	AA29-30002N	FILTER-LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ LX802S	AA29-30002N	FILTER-LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ NT802S	1404-001045	THERMISTOR-NTC;4.7OHM,15%,2900K,35.0MW,T	
⚠ P801S	1404-001156	THERMISTOR-PTC;9OHM,+30%/-20%,220VRMS,27	
⚠ PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
Q201	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q202	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q203	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q204	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q206	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q207	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q208	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q209	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q210	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q211	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q212	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q213	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q222	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q402A	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L,	
Q501	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q602	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q901	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q902	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q903	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q904	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q905	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q906	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q907	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q908	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q909	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
Q910	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
R102	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R103	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R105	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R106	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R201	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R202	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R203	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R204	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R205	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R206	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R207	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R208	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R209	2001-000221	R-CARBON;1.2OHM,5%,1/8W,AA,TP,1.8X3.2M	
R210	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R211	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R212	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R213	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R214	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R215	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R216	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R222	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R223	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R224	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R225	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R226	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R228	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
R231	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R232	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R233	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R234	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R235	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R236	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R237	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R238	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R239	2001-001159	R-CARBON(S);510OHM,5%,1/2W,AA,TP,2.4X6.4	
R241	2001-000343	R-CARBON;1300HM,5%,1/8W,AA,TP,1.8X3.2MM	
R245	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R246	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R248	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R249	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R250	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R251	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R252	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R253	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R254	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R255	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R256	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R258	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R259	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R260	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R261	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R262	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R263	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R264	2001-000534	R-CARBON;240OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R265	2001-000534	R-CARBON;240OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R267	2001-000534	R-CARBON;240OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R301	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
R302	2004-001984	R-METAL(S);26.7Kohm,1%,1/2W,AA,TP,2.4x6.	
R303	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R304	2008-001013	R-FUSIBLE(S);1.2ohm,5%,2W,AF,TP,3.9x10mm	
R305	2003-002182	R-METAL OXIDE(S);470ohm,5%,2W,AG,TP,3.9x	
R306	2003-002182	R-METAL OXIDE(S);470ohm,5%,2W,AG,TP,3.9x	
R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R313	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R314	2004-001986	R-METAL(S);35.7Kohm,1%,1/2W,AA,TP,2.4x6.	
R315	2004-004970	R-METAL(S);62Kohm,1%,1/8W,AA,TP,1.8x3.2m	
R401	2003-002186	R-METAL OXIDE(S);22Kohm,5%,2W,AG,TP,3.9x	
R402	2003-002186	R-METAL OXIDE(S);22Kohm,5%,2W,AG,TP,3.9x	
R403	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
R404	2001-001037	R-CARBON(S);0.39OHM,5%,1/2W,AA,TP,2.4X6.	
R405	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
R407	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
R408	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
R409	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
R410	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
R412	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
R414	2001-001165	R-CARBON(S);56OHM,5%,1/2W,AA,TP,2.4X6.4M	

Loc. No.	Code No.	Description ; Specification	Remark
R424	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
R425	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
R428	2001-001106	R-CARBON(S);220KOHM,5%,1/2W,AA,TP,2.4X6.	
R429	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
R432	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
R433	2008-001127	R-FUSIBLE(S);6.8Kohm,5%,1W,AF,TP,3.9X10m	
R434	2003-000664	R-METAL OXIDE(S);33ohm,5%,2W,AF,TP,4x12m	
R436	2003-002151	R-METAL OXIDE;18KOHM,5%,2W,AG,TP,6X16MM	
R437	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
R438	2001-001131	R-CARBON(S);33KOHM,5%,1/2W,AA,TP,2.4X6.4	
R501	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R502	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R503	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R504	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R505	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R506	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R507	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
R508	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R509	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
R510	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
R511	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R512	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
R513	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
R514	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
R517	2001-001077	R-CARBON(S);150OHM,5%,1/2W,AA,TP,2.4X6.4	
R518	2001-001185	R-CARBON(S);750OHM,5%,1/2W,AA,TP,2.4X6.4	
R519	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R520	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R521	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R522	2008-000290	R-FUSIBLE(S);2.4ohm,5%,2W,AF,TP,3.9X10MM	
R524	2008-000299	R-FUSIBLE(S);47ohm,5%,2W,AF,TP,3.9x10mm	
R525	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
R526	2002-001009	R-COMPOSITION;2.7Kohm,10%,1/2W,AA,TP,3.7	
R529	0403-001316	DIODE-ZENER;MTZJ3.0A,2.85-3.07V,500mW,DO	
R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R604	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
R605	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
R606	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R607	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R608	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R609	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R613	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R614	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R615	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R616	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R617	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R619	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R620	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R621	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R622	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R623	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R624	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R625	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R626	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R666	2009-000022	R-METAL PLATE;0.47ohm,10%,5W,CL,TP,5x14x	
R701	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R702	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R703	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R704	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R705	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R706	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R707	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R708	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R709	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R710	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R715	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R716	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R719	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R723	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R730	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R731	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R802	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
R803	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
R804	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
R807	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
R808	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
R809	2001-000022	R-CARBON(S);33OHM,5%,1/2W,AA,TP,2.4X6.4M	
R810	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4	
R811	2001-001149	R-CARBON(S);43KOHM,5%,1/2W,AA,TP,2.4X6.4	
R812	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R813	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
R815	2001-001086	R-CARBON(S);18KOHM,5%,1/2W,AA,TP,2.4X6.4	
R816	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
R817	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
R818	2001-001113	R-CARBON(S);270KOHM,5%,1/2W,AA,TP,2.4X6.	
R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
R821	2004-004089	R-METAL(S);123Kohm,1%,1/2W,AA,TP,2.5x6.5	
R822	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R823	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R824	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R825	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
R826	2001-001072	R-CARBON(S);12OHM,5%,1/2W,AA,TP,2.4X6.4M	
R827	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
R828	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
R829	2003-001036	R-METAL OXIDE(S);3.3ohm,5%,2W,AF,TP,3.9x	
R831	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R832	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
R835	2003-002211	R-METAL OXIDE(S);91Kohm,5%,2W,AG,TP,3.9x	
R836	2003-002211	R-METAL OXIDE(S);91Kohm,5%,2W,AG,TP,3.9x	
R901	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R902	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R903	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R904	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R905	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R906	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R907	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R908	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R909	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R910	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R911	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R912	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R913	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R914	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R915	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R916	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R917	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R918	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R919	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R920	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R921	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R922	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R923	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R924	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R925	2001-001035	R-CARBON;91OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R929	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R930	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R931	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R932	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R933	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R934	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R935	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R937	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R938	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R939	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
R940	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R941	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R942	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R943	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R944	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R945	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R946	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R947	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R948	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R952	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R953	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	

Loc. No.	Code No.	Description ; Specification	Remark
RM901	AA59-60001U	MODULE-REMOCON;-,ORC-50VF/SR-12V,38KHz,9	
⚠ RP801S	2002-001010	R-COMPOSITION;1.8Mohm,5%,1/2W,AA,TP,3.7x	
⚠ RR430S	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
⚠ RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ RY801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ RY802S	2002-001013	R-COMPOSITION;4.7Mohm,5%,1/2W,AA,TP,3.7x	
⚠ SW801S	3403-000179	SWITCH-PUSH;250V,5A,DPST,-,JPW-2104B	
SW901	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW902	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW903	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW904	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW905	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
⚠ T401A	AA26-50001B	TRANS-HORIZ.DRIVE;-,7.1mH,102uH,10-20uH,	
⚠ T444S	AA26-00066A	TRANS FBT;-,FSV-14B003C(S),20/21,125V	
⚠ T801S	AA26-00064A	TRANS SWITCHING;CODE-NO,CT-15A8,-,AC90~2	
⚠ TU01S	AA40-00060A	TUNER-F/S;TCPS3001PD09D(S),-,PAL-M(NTSC)	
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
⚠ VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
X201	2801-003432	CRYSTAL-UNIT;20.25MHZ,30PPM,28-AAM,13PF,	
X601	2801-003903	CRYSTAL-UNIT;18.432MHz,25ppm,28-AAM,12pF	
X901	2801-003728	CRYSTAL-UNIT;6MHz,30ppm,28-AAM,20pF,40oh	
	AA39-20010B	LEAD CONNECTOR-ASSY;-,YFH800-01,S,1P,500	
	AA39-20010H	LEAD CONNECTOR-ASSY;-,YFH800-01,S,1P,300	
	AA39-20536D	LEAD CONNECTOR-ASSY;-,F,F,1P,50MM,1617#2	
	AA65-30009A	CLAMP-FBT;ABS,V0,BLK,-,-,-	
	AA65-30109A	CLAMP-FBT;NYLON-66,V2,BLK,-,-,-	
	AA65-30110A	CLAMP-WIRE;NYLON 66,V2,BLK,PAL TVI,ALL M	
	AA99-10177H	ASSY-PCB MAIN,AUTO; AA99-30181W ,V	
	AA41-00132B	PCB-MAIN;CT-21A8,FR-1,1L,B,1.6T,330x245	
	AA39-20536B	LEAD CONNECTOR-ASSY;-,-,-,-,-,-,-,-,-,F,	
	AA65-30018A	CLAMP-WIRE;NYLON-66,-,-,DATL-600,DONG-A,	

ASSY CABINET FRONT

	* AA91-00393D	ASSY CABINET FRONT;-,15A8 EL,(SPK)S907P+	
	* AA90-00317F	ASSY CABINET;15A8,CS15A8WT7X/SAP	
AV+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	
CB+CF	6003-001025	SCREW-TAPTITE;RH,+,B,M4,L20,ZPC(BLK),SWR	
CB+JCK	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
CRT+CF	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC	
KC+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
PCB	AA64-01230B	INLAY-COVER;D2,D3,PVC-SHEET,T0.4,94V0,-,	
SPK+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
WIN+CF	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
	AA64-00869D	CABINET BACK;15A8,-,HIPS,V0,BLK	
	AA64-00892B	INLAY BACK;D2,D3,RCA9P,PS SHEET,T0.3,BLK	
	AA65-30008A	CLAMP-CORD;PE,HB,BLK,-,-,-	
	AA65-30107A	CLAMP-D,COIL;NYLON 66,V2,NTR,-,20~22 INC	
	AA61-40113A	STOPPER-PCB;501H,HIPS,NTR,HB,-,-	
	AA61-60003J	SPRING-CS;-,SUS304,0.5,OD6,H12,N7,-,-,-	
	AA64-00812B	KNOB CONTROL;-,21A8,-,ABS,HB,G3676	
	AA64-00814B	KNOB POWER;-,21A8,-,ABS,HB,G3676	
	AA64-00816B	WINDOW REMOCON;-,21A8,-,PC,V0,VIOLET,-	
	AA64-00818B	INDICATOR LED;-,21A8,-,ACRYL,-,CLR,-	
	AA64-00868C	CABINET FRONT;15A8,SV907P+DB004P ELP,HIP	
	AA64-70127A	BADGE-BRAND;AL,FLAT,SILVER,L=40,SAMSUNG,	
	AA65-00011B	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,NTR,15M	
	AA96-00380A	ASSY SPEAKER;-,16ohm,5W,3001-001072,350/	
	3001-001072	SPEAKER;5W,16ohm,90dB,180Hz	
	AA39-00102D	LEAD CONNECTOR-ASSY;-,-,-,-,-,-,-,-,-,35	

ASSY ACCESSORY

	* AA94-02306E	ASSY ACCESSORY;CS21S5NT7X/SAP,KS2A,SINGA	
	AA26-90002A	TRANS-MATCHING;-,75-300OHM,PAL,40-890MHZ	
	AA68-00886B	MANUAL USERS;-,-,ENG,-,W/P100G,-,-,B5,-,	
	AA42-00003A	ANT ROD;-,3S,620,ABS,UL/CSA	

Loc. No.	Code No.	Description ; Specification	Remark

ASSY CRT

	* AA94-02570A	ASSY CRT;AA03-00188A,-300mG,A36QDT351X(	
	AA27-00069A	DEFLECTION-YOKE;-,DIF-1592CA,15,ST,2.0mH	
	AA63-60028A	SPACER-DY;NEOPRENE,-,BLK,V0 W12,-,-	
	AA27-00002A	MAGNET-CONVERGENCE;-,JH291-SC-OB,29.1MM	
	AA03-00188A	CRT COLOR;A36QDT351X(S),15DF,15INCH,0.6,	

ASSY-PCB,A/V FRONT

	* AA95-00631A	ASSY-PCB,A/V FRONT;-,CT-21A8,KS2A,-,-,-	
CA02	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
CA03	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
CA04	2202-000720	C-CERAMIC,MLC-AXIAL;8.2nF,20%,16V,Y5R,TP	
CA05	2202-000720	C-CERAMIC,MLC-AXIAL;8.2nF,20%,16V,Y5R,TP	
CA06	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
CA07	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
CN01A	AA39-20068E	LEAD CONNECTOR-ASSY;-,YBNH025-08,67096-0	
CN05A	AA39-20069D	LEAD CONNECTOR-ASSY;-,YBNH025-05,67096-0	
CN06A	AA39-00070A	LEAD CONNECTOR-ASSY;-,-,-,-,-,-,-,-,-,YB	
JE01	3722-000143	JACK-PHONE;1P(VER),3.4mm,AG,BLK,NO	
JR01	3722-001031	JACK-RCA;3P,3.6MM,#18,AU	
LA04	2701-000180	INDUCTOR-AXIAL;33uH,5%,2.5x3.4mm	
LA05	2701-000180	INDUCTOR-AXIAL;33uH,5%,2.5x3.4mm	
PCB	AA41-10358B	PCB-A/V FRONT;SCT12A,1,FR-1,245x245x1.6T	
RA01	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
RA02	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	

ASSY-POWER,CORD

	* AA96-20109C	ASSY-POWER,CORD;-,CP2/NO(4.0),H/C300,KKP	
	AA39-10006X	POWER-CORD;-,KKP419C,KLCE-2F,2.286MT,3P,	
	AA61-20284A	HOLDER;-,P-CORD,PP,VO,BLK,KE-002	

REMOCON

	* AA59-00104A	REMOCON;-,TM59,DREAM,29,L/GRAY,-,EX,PA	

7-2 CS21A9W7X/BWT

ASSY PCB MAIN(OPT)

* AA94-02072UASSY PCB MAIN(OPT);CS21A9W7X/BWT,KS2A,RU

Loc. No.	Code No.	Description ; Specification	Remark
C102	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
C103	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C104	2401-000142	C-AL;1000uF,20%,16V,WT,TP,10x20,5	
C105	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C106	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C115	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C116	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C201	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
C202	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C203	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C206	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C211	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C212	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
C213	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
C214	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C215	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C216	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C217	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
C218	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C219	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C220	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C221	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C222	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C223	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C224	2201-002031	C-CERAMIC,DISC;0.005nF,0.5pF,50V,NP0,TP,	
C225	2201-002031	C-CERAMIC,DISC;0.005nF,0.5pF,50V,NP0,TP,	
C226	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C228	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
C229	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C231	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C232	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C233	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
C234	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
C235	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
C236	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
C237	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
C239	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C242	2301-000310	C-FILM,PEF;68nF,5%,50V,TP,8.0X8.5X4.0X5,	
C243	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C244	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C245	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C247	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C301	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C302	2401-000326	C-AL;100uF,20%,35V,GP,TP,8x11.5,5	
C303	2201-002031	C-CERAMIC,DISC;0.005nF,0.5pF,50V,NP0,TP,	
C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
C305	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
C306	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C308	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C401	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
C403	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
C404	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
C407	2301-001338	C-FILM,MPE-PPF;0.68nF,5%,1.6kV,TP,28x7x1	
C408	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
C411	2301-000104	C-FILM,PEF;1.2nF,5%,50V,TP,6.5x3.0x5.5mm	
C412	2301-000188	C-FILM,PEF;1nF,5%,100V,TP,10.5x12.5x6.5,	
C414	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
C415	2301-000314	C-FILM,PEF;8.2nF,5%,50V,TP,6.5x3.0x5.5mm	
C416	2301-000289	C-FILM,PEF;5.6nF,5%,50V,TP,7x6x3,5	
C417	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C418	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
C419	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C420	2301-001065	C-FILM,MPPF;47nF,5%,630V,TP,19x15.5x7,7.	
C421	2201-000556	C-CERAMIC,DISC;0.47nF,10%,500V,Y5P,TP,5.	
C422	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
C424	2201-000132	C-CERAMIC,DISC;0.1nF,10%,500V,Y5P,TP,6.5	
C427	2401-002267	C-AL;2.2uF,20%,250V,GP,TP,8x11.5,5	
C429	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
C501	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.	
C502	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.	
C503	2202-000205	C-CERAMIC,MLC-AXIAL;22pF,5%,50V,SL,TP,1.	
C504	2305-000704	C-FILM,MPEF;100nF,5%,250V,TP,16.5x10.3x5	
C505	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C506	2305-000704	C-FILM,MPEF;100nF,5%,250V,TP,16.5x10.3x5	
C507	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C508	2305-000704	C-FILM,MPEF;100nF,5%,250V,TP,16.5x10.3x5	
C509	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C511	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
C512	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
C513	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
C514	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
C515	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5	
C516	2201-002063	C-CERAMIC,DISC;10nF,+80-20%,3KV,Y5V,TP,1	
C605	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C607	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C608	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C609	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C610	2301-000314	C-FILM,PEF;8.2nF,5%,50V,TP,6.5x3.0x5.5mm	
C611	2301-000314	C-FILM,PEF;8.2nF,5%,50V,TP,6.5x3.0x5.5mm	
C612	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
C613	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
C617	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
C620	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C621	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
C622	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C623	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C624	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C625	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C626	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C627	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C628	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C629	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C630	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C631	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C632	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C634	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C635	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C636	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
C637	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C638	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C639	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C640	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C641	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C642	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C643	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C644	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C645	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C646	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C647	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
C648	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
C650	2201-000558	C-CERAMIC,DISC;0.47nF,10%,50V,Y5P,TP,5x3	
C652	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C654	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
C656	2201-000304	C-CERAMIC,DISC;0.001nF,0.25pF,50V,NP0,TP	
C657	2201-000304	C-CERAMIC,DISC;0.001nF,0.25pF,50V,NP0,TP	
C660	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C701	2202-000231	C-CERAMIC,MLC-AXIAL;330pF,10%,50V,Y5P,TP	
C707	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
C708	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
C803	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
C804	2201-000332	C-CERAMIC,DISC;2.2nF,20%,250V,Y5U,TP,9x4	
C805	2201-000332	C-CERAMIC,DISC;2.2nF,20%,250V,Y5U,TP,9x4	
C806	2401-003031	C-AL;470uF,20%,450V,GP,BK,35x45mm,1	
C807	2301-001342	C-FILM,PPF;1.5nF,5%,800V,TP,15x6.5x11.5m	
C808	2401-002300	C-AL;47uF,20%,50V,GP,TP,6.3x11,5	
C809	2301-000356	C-FILM,PEF;47nF,5%,50V,TP,7.5x4.0x6.5,5m	
C811	2301-000310	C-FILM,PEF;68nF,5%,50V,TP,8.0X8.5X4.0X5,	
C814	2201-000991	C-CERAMIC,DISC;0.56nF,10%,2kV,Y5P,TP,7.5	
C815	2401-003026	C-AL;330uF,20%,200V,GP,ST,22x35,10	

Loc. No.	Code No.	Description ; Specification	Remark
C816	2401-000293	C-AL;100uF,+30-10%,200V,GP,TP,16x25	
C817	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C818	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
C819	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C820	2401-001054	C-AL;3300uF,20%,25V,GP,TP,18x25,7.5	
C821	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
C822	2201-000599	C-CERAMIC,DISC;0.56nF,10%,500V,Y5P,TP,5.	
C823	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C825	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C826	2401-001363	C-AL;470uF,20%,16V,GP,TP,10x12.5,5	
C827	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C829	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C831	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C832	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C835	2401-002286	C-AL;470uF,20%,16V,WT,TP,10x12.5,5	
C837	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C838	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C839	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C840	2401-002235	C-AL;10uF,20%,16V,GP,TP,5x11mm,5mm	
C841	2401-000611	C-AL;1uF,20%,50V,WT,TP,5x11,5	
C843	2201-000681	C-CERAMIC,DISC;0.082nF,5%,50V,SL,TP,5x3,	
C901	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C902	2401-000553	C-AL;1uF,10%,50V,GP,TP,5x11,5	
C904	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
C905	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
C907	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C908	2202-000863	C-CERAMIC,MLC-AXIAL;560pF,10%,50V,Y5P,TP	
C910	2201-000980	C-CERAMIC,DISC;0.03nF,5%,50V,NP0,TP,5x3,	
C911	2201-000980	C-CERAMIC,DISC;0.03nF,5%,50V,NP0,TP,5x3,	
C913	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
C914	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C915	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
C916	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C917	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C918	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C919	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C920	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
C921	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
CG501	AA27-00084A	COIL;S-23,-,-,-,-,-,-,S-23,5000Mohm	
CG502	AA27-00084A	COIL;S-23,-,-,-,-,-,-,S-23,5000Mohm	
CG503	AA27-00084A	COIL;S-23,-,-,-,-,-,-,S-23,5000Mohm	
CLAMP1	AA65-30018A	CLAMP-WIRE;NYLON-66,-,-,DATL-600,DONG-A,	
CLAMP2	AA65-30018A	CLAMP-WIRE;NYLON-66,-,-,DATL-600,DONG-A,	
CN501B	AA39-20054A	LEAD CONNECTOR-ASSY;-,YBNH025-06,S,6P,40	
CN502B	AA39-20053A	LEAD CONNECTOR-ASSY;-,YBNH025-05,S,5P,40	
CN602	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
CN701	3711-002647	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
CR401S	2306-000326	C-FILM,MPPF;4.7nF,5%,1.6KV,TP,28.5x16x9m	
CR402S	2303-001015	C-FILM,PPF;5.5nF,5%,1.6kV,TP,29x9.5x17,2	
CR403S	2303-001001	C-FILM,PPF;22nF,5%,630V,TP,18x14.5x8.5mm	
CR404S	2306-000235	C-FILM,MPPF;560nF,5%,400V,TP,26*22.5*14,	
CR405S	2306-000195	C-FILM,MPPF;360nF,5%,400V,TP,26x19x11.5,	
CW901	2503-000156	C-NETWORK;100pFx4,20%,50V	
CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
CX802S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
CY802S	2201-000446	C-CERAMIC,DISC;3.3nF,20%,400V,Y5U,TP,15x	
D201	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D202	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D203	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D204	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D205	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D206	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D207	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D208	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D209	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D210	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D212	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
D401	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
D402	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
D406	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D407	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
D408	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
D410	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
D411	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
D413	0402-000537	DIODE-RECTIFIER;RH1A,600V,0.6A,DO-204AC	
D502	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D602	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D801	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
D801S	0402-000549	DIODE-BRIDGE;RBV606,600V,6A,-,BK	
D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
D804	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D808	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D810	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D811	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D813	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
D816	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
D901	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D902	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D903	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D904	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D905	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
D906	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
D907	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
D908	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
DDR01	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	H/SINK
DDR01	0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220	H/SINK
DDR01	1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	H/SINK
DH01	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	H/SINK
DH01	0502-001136	TR-POWER;KSD5703,NPN,70W,TO-3PF,ST,8-	H/SINK
DZ201	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ202	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ203	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ204	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
DZ304	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
DZ305	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
DZ306	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
DZ401	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
DZ402	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
DZ501	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
DZ502	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
DZ601	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ602	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ603	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
DZ801	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
DZ802	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ803	0403-001167	DIODE-ZENER;MTZJ30D,30V,29.02-30.51V,500	
DZ804	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
DZ805	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
DZ806	0403-000714	DIODE-ZENER;MTZJ3.3B,3.3V,3.32-3.53V,500	
DZ808	0403-000719	DIODE-ZENER;MTZJ7.5B,7.5V,7.07-7.45V,500	
DZ901	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ902	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ903	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ904	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ905	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ906	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
DZ907	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
FD801S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
FD802S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
FD803S	3601-001086	FUSE-AXIAL LEAD;125V,5A,FAST-ACTING,GLAS	
FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
IC201S	1204-001632	IC-VIDEO PROCESS;VDP3108B-C3,DIP,64P,-,P	
IC301	1204-000517	IC-VERTIVAL DEF.;LA7845,SIP,7P,-,PLASTIC	H/SINK
IC401	1202-000103	IC-VOLTAGE COMP.;393,DIP,8P,300MIL,DUAL,	
IC501	1201-000539	IC-VIDEO AMP;6101,ZIP,9P,-,SINGLE,-,PLAS	
IC502	1201-000539	IC-VIDEO AMP;6101,ZIP,9P,-,SINGLE,-,PLAS	
IC503	1201-000539	IC-VIDEO AMP;6101,ZIP,9P,-,SINGLE,-,PLAS	
IC601	1204-001715	IC-SOUND PROCESSOR;MSP3400D-C5,DIP,52P,5	
IC602	1201-001064	IC-POWER AMP;7297,ZIP,15P,-,DUAL,32DB,PL	H/SINK
IC801S	1203-001482	IC-PWM CONTROLLER;3S1265R,TO-3P,5P,210,P	H/SINK
IC803	1203-001697	IC-VOLTAGE REGULATOR;78R08,TO-220,4P,-,P	
IC804	1203-000284	IC-POSI.FIXED REG.;7806,TO-220,3P,-,PLAS	H/SINK
IC901	AA09-00041A	IC-MCU;SDA555X-OTP,SDA555X-OTP,-,-,52	
IC902	1103-001171	IC-EEPROM;24L161,16KBIT,DIP,8P,300MIL,10	
IC903	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
IC904	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	

Loc. No.	Code No.	Description ; Specification	Remark
J111	0401-000005	DIODE-SWITCHING;1N4148,100V,200MA,DO-35,	
J239	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
J501	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
J625	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
J699	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
J909	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JA701	3722-000195	JACK-SCART;42P,-,SN,BLK,NO	
L102	2701-000200	INDUCTOR-AXIAL;5.6uH,10%,4.2x9.8mm	
L103	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
L201	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L202	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L203	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L204	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L209	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
L301	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L302	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L303	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L401	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L402	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
L405	AA27-00057A	COIL HORIZ. WIDTH;-,10mH,YL-9N 15x27.5 C	
L406	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L407	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
L408	AA27-00038A	COIL-HORIZ.WIDTH;-,700UH,15X27,-,BK	
L601	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
L602	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L603	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L604	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
L605	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L606	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L607	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L608	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L609	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm	
L610	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L705	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L706	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
L801	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L804	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
L806	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L807	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
L808	AA27-10002L	COIL-CHOKE;-,24UH,K,-,2A,-,24UH-K,10X10M	
L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
L901	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
L903	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
L904	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
L905	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L906	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
⚠ LC801S	AA27-20004A	COIL-DEGAUSSING;-,21,14ohm,45T,L2380,E	
LD901	AA96-30001B	ASSY-LED,GUIDE;-,AA61-50055A,DL-G5RGA,-	
⚠ LR401S	AA27-00075A	COIL LINEARITY;-,50uH,DR14x20,11mm,18x38	
⚠ LX801S	AA29-30002N	FILTER-LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ LX802S	AA29-30002N	FILTER-LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ NT802S	1404-001045	THERMISTOR-NTC;4.7OHM,15%,2900K,35.0MW,T	
⚠ P801S	1404-000002	THERMISTOR-PTC;9ohm,20%,-,-,TR,RECT,-	
⚠ PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
Q201	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q202	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q203	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q204	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q206	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q207	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q208	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q209	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q210	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q211	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q212	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q213	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q222	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q402	0502-001007	TR-POWER;KSC2073-H2,NPN,25W,TO-220,ST,6	
Q404	0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,	
Q405	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q501	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q602	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	

Loc. No.	Code No.	Description ; Specification	Remark
Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L,	
Q902	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q903	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q904	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q905	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q906	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q907	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q908	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
Q909	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
Q910	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
R102	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R103	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R105	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R106	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R201	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R202	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R203	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R204	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R205	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R206	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R207	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R208	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R209	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R210	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R211	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R212	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R213	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R214	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R215	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R216	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R222	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R223	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R224	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R225	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R226	2001-000628	R-CARBON;300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R228	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
R231	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R232	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R233	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R234	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R235	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R236	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R237	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R238	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R239	2001-001114	R-CARBON(S);2700HM,5%,1/2W,AA,TP,2.4X6.4	
R241	2001-000343	R-CARBON;130OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R245	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R246	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R248	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R249	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R250	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R251	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R252	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R253	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R254	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R255	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R256	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R258	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R259	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R260	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R261	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R262	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R263	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R264	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R265	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R267	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R301	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
R302	2004-001984	R-METAL(S);26.7Kohm,1%,1/2W,AA,TP,2.4x6.	
R303	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R304	2008-001013	R-FUSIBLE(S);1.2ohm,5%,2W,AF,TP,3.9x10mm	
R305	2003-002182	R-METAL OXIDE(S);470ohm,5%,2W,AG,TP,3.9x	
R306	2003-002182	R-METAL OXIDE(S);470ohm,5%,2W,AG,TP,3.9x	
R309	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R310	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R313	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R314	2004-001986	R-METAL(S);35.7Kohm,1%,1/2W,AA,TP,2.4x6.	
R315	2004-004970	R-METAL(S);62Kohm,1%,1/8W,AA,TP,1.8x3.2m	

Loc. No.	Code No.	Description ; Specification	Remark
R401	2003-002186	R-METAL OXIDE(S);22Kohm,5%,2W,AG,TP,3.9x	
R402	2003-002186	R-METAL OXIDE(S);22Kohm,5%,2W,AG,TP,3.9x	
R403	2003-002037	R-METAL OXIDE(S);270ohm,5%,2W,AF,TP,3.9x	
R405	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
R407	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
R408	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
R409	2001-001165	R-CARBON(S);56OHM,5%,1/2W,AA,TP,2.4X6.4M	
R410	2001-001192	R-CARBON(S);820OHM,5%,1/2W,AA,TP,2.4X6.4	
R411	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R412	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
R413	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
R414	2001-001165	R-CARBON(S);56OHM,5%,1/2W,AA,TP,2.4X6.4M	
R415	2001-001054	R-CARBON(S);1.6KOHM,5%,1/2W,AA,TP,2.4X6.	
R417	2004-001893	R-METAL(S);22Kohm,1%,1/2W,AA,TP,2.5x6.5m	
R418	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
R420	2001-001168	R-CARBON(S);6.8KOHM,5%,1/2W,AA,TP,2.4X6.	
R421	2001-001144	R-CARBON(S);4.7KOHM,5%,1/2W,AA,TP,2.4X6.	
R424	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
R425	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
R427	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
R428	2001-001106	R-CARBON(S);220KOHM,5%,1/2W,AA,TP,2.4X6.	
R429	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
R432	2004-001397	R-METAL(S);4.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
R433	2008-001127	R-FUSIBLE(S);6.8Kohm,5%,1W,AF,TP,3.9X10m	
R434	2003-000664	R-METAL OXIDE(S);33ohm,5%,2W,AF,TP,4x12m	
R436	2003-002151	R-METAL OXIDE;18KOHM,5%,2W,AG,TP,6X16MM	
R437	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
R438	2001-001131	R-CARBON(S);33KOHM,5%,1/2W,AA,TP,2.4X6.4	
R440	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R441	2001-001144	R-CARBON(S);4.7KOHM,5%,1/2W,AA,TP,2.4X6.	
R501	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R502	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R503	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R504	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R505	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R506	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R507	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
R508	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R509	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
R510	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
R511	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R512	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
R513	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
R514	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
R516	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
R517	2001-001077	R-CARBON(S);150OHM,5%,1/2W,AA,TP,2.4X6.4	
R518	2001-001185	R-CARBON(S);750OHM,5%,1/2W,AA,TP,2.4X6.4	
R519	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R520	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R521	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R522	2008-000206	R-FUSIBLE(S);1ohm,5%,1/2W,AF,TP,2.5x6.5m	
R523	2008-000206	R-FUSIBLE(S);1ohm,5%,1/2W,AF,TP,2.5x6.5m	
R524	2008-000299	R-FUSIBLE(S);47ohm,5%,2W,AF,TP,3.9x10mm	
R525	2001-001062	R-CARBON(S);10MOHM,5%,1/2W,AA,TP,2.4X6.4	
R526	2002-001009	R-COMPOSITION;2.7Kohm,10%,1/2W,AA,TP,3.7	
R529	0403-001316	DIODE-ZENER;MTZJ3.0A,2.85-3.07V,500mW,DO	
R601	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R602	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R603	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R604	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
R605	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
R606	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R607	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R608	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R609	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R613	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R614	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R615	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R616	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R617	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R619	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R620	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R621	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R622	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R623	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R624	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R625	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R626	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R666	2009-001011	R-METAL PLATE;0.18ohm,10%,5W,CL,TP,5x14x	
R701	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R702	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R703	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R704	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R705	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R706	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R707	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R708	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R709	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R710	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R715	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R716	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R717	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R718	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R719	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R723	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R730	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R731	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
R802	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
R803	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
R804	2003-001025	R-METAL OXIDE(S);15Kohm,5%,2W,AF,TP,3.9x	
R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
R807	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
R808	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
R809	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
R810	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4	
R811	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
R812	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R813	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
R816	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
R817	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
R818	2001-001113	R-CARBON(S);270KOHM,5%,1/2W,AA,TP,2.4X6.	
R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
R821	2004-001889	R-METAL(S);127Kohm,1%,1/2W,AA,TP,2.5x6.5	
R822	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R823	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R824	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R825	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
R826	2001-001072	R-CARBON(S);12OHM,5%,1/2W,AA,TP,2.4X6.4M	
R827	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
R828	2008-000266	R-FUSIBLE(S);1ohm,5%,2W,AF,TP,3.9x10mm	
R829	2003-001036	R-METAL OXIDE(S);3.3ohm,5%,2W,AF,TP,3.9x	
R831	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R832	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
R833	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R835	2003-002211	R-METAL OXIDE(S);91Kohm,5%,2W,AG,TP,3.9x	
R836	2003-002211	R-METAL OXIDE(S);91Kohm,5%,2W,AG,TP,3.9x	
R901	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R902	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R903	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R904	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R905	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R906	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R907	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R908	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R909	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R910	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R911	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R912	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R913	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R914	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R915	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R916	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R917	2001-000878	R-CARBON;6.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R918	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R919	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R920	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R921	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R922	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc. No.	Code No.	Description ; Specification	Remark
R923	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R924	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R925	2001-001035	R-CARBON;91OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R926	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R929	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R930	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R931	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R932	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R933	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R934	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R935	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R937	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R938	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R939	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
R940	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
R941	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
R942	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
R943	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R944	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
R945	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
R946	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R947	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R948	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R952	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R953	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
⚠ RL801S	3501-001040	RELAY-POWER;12VDC,500mW,10A,1FormA,15mS,	
RM901	AA59-60001U	MODULE-REMOCON;-,ORC-50VF/SR-12V,38KHz,9	
⚠ RP801S	2002-001010	R-COMPOSITION;1.8Mohm,5%,1/2W,AA,TP,3.7x	
⚠ RR430S	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
⚠ RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ RY801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ RY802S	2002-001013	R-COMPOSITION;4.7Mohm,5%,1/2W,AA,TP,3.7x	
⚠ SW801S	3403-000179	SWITCH-PUSH;250V,5A,DPST,-,JPW-2104B	
SW901	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW902	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW903	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW904	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
SW905	3404-000244	SWITCH-TACT;15V,20mA,90-170gf,7.5x7mm,SP	
⚠ T401	AA26-50001R	TRANS-HORIZ.DRIVE;-,80MH,520UH,4UH,G11A	
⚠ T444S	AA26-00057A	TRANS-FBT;-,FUH-29A001B(S),25/29,130	
⚠ T801S	AA26-00044A	TRANS SWITCHING;-,-,-,AC90~260V,DC135/15	
⚠ TU01S	AA40-00060A	TUNER-F/S;TCPS3001PD09D(S),-,PAL-M(NTSC)	
⚠ V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
⚠ VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
X201	2801-003432	CRYSTAL-UNIT;20.25MHZ,30PPM,28-AAM,13PF,	
X601	2801-003903	CRYSTAL-UNIT;18.432MHz,25ppm,28-AAM,12pF	
X901	2801-003728	CRYSTAL-UNIT;6MHz,30ppm,28-AAM,20pF,40oh	
	AA39-20010B	LEAD CONNECTOR-ASSY;-,YFH800-01,S,1P,500	
	AA39-20010H	LEAD CONNECTOR-ASSY;-,YFH800-01,S,1P,300	
	AA65-30009A	CLAMP-FBT;ABS,V0,BLK,-,-,-	
	AA65-30109A	CLAMP-FBT;NYLON-66,V2,BLK,-,-,-	
	AA99-10177C	ASSY-PCB MAIN,AUTO; AA99-30181R ,V	
	AA41-00132B	PCB-MAIN;CT-21A8,FR-1,1L,B,1.6T,330x245	
	AA65-30105A	CLAMP-WIRE;NYLON 66,V2,NTR,15MM,ALL MODE	
	AA61-00462B	SUPPORT-HEAT SINK;21A9,ABS,GRAY,VO,-,-,-	

ASSY CABINET FRONT

	* AA90-00356C	ASSY CABINET;21A9,CS21A9W7X/BWT	
	* AA91-00444C	ASSY CABINET FRONT;-,21A9 CIS,S704P+B702	
AV+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	
BACK	AA63-60001X	SPACER-FELT;FELT,T0.5,BLK,330X15,-,-	
CB+CF	6003-001025	SCREW-TAPTITE;RH,+,B,M4,L20,ZPC(BLK),SWR	
CB+JCK	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
CF+PC	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	
KC+PC	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
PCB	AA64-01230B	INLAY-COVER;D2,D3,PVC-SHEET,T0.4,94V0,-,	
SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	
WIN+PC	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
	AA60-10050R	SCREW-ASSY;WC,HH,+,M5,L31.5,SWRCH18A,ZPC	
	AA64-00894B	INLAY BACK;D2,D3,SCART(2),PS SHEET,T0.3,	
	AA64-01155D	CABINET BACK;21A9,-,HIPS,V2,BLK	
	AA65-00009B	CLAMP-D,COIL;NYLON 66,V0,-,-,21A8,-	

Loc. No.	Code No.	Description ; Specification	Remark
	AA65-30008A	CLAMP-CORD;PE,HB,BLK,-,-,-	
	AA69-30032D	BAG-SHEET;HDPE+PE FOAM,-,W1200,H1200,-,-	
	AA61-40113A	STOPPER-PCB;501H,HIPS,NTR,HB,-,-	
	AA61-60003J	SPRING-CS;-,SUS304,0.5,OD6,H12,N7,-,-,-	
	AA64-00820E	CABINET FRONT;21A9,S704P+B702P MLP,HIPS,	
	AA64-00821E	PANEL CONTROL;21A9 ,HIPS,-,HB,G4309,-,SV	
	AA64-00823B	KNOB CONTROL;-,21A9,-,ABS,HB,G3676	
	AA64-00825B	KNOB POWER;-,21A9,-,ABS,HB,G3676	
	AA64-00827B	WINDOW REMOCON;21A9,PC,-,-,-,V0,VIOLET,-	
	AA64-00829B	INDICATOR LED;21A9,ACRYL,-,CLR,-,-,-	
	AA64-70123A	BADGE-BRAND;AL,SAMSUNG,SILVER,L=50,FLAT,	
	AA65-00011B	CLAMP-WIRE;ALL MODEL,NYLON 66,V2,NTR,15M	

ASSY CRT

	* AA94-02328A	ASSY CRT;A51CSH196X03,+380MG,21,ITC,-,-	
	AA03-00128A	CRT;-,A51LSH196X03,+380mG,21INCH,9	

ASSY ACCESSORY

	* AA94-02518A	ASSY ACCESSORY;CS21A9W7X/BWT,KS2A,RUSSIA	
	AA26-90001C	TRANS-MATCHING;-,300ohm/75ohm,PAL,40-890	
	AA68-01012A	MANUAL-USER;-,BWT,RUS,40P,-,W/P100(G),1,	
	AA63-00241B	COVER-AV;21A9,HIPS,-,HB,G4309,SV704P,-	
	AA42-00003A	ANT ROD;-,3S,620,ABS,UL/CSA	
	AA68-01120A	MANUAL SERVICE;-,-,CIS,A4,6PAGE(FOLD),W/	

ASSY-PCB,A/V FRONT

	* AA95-00631A	ASSY-PCB,A/V FRONT;-,CT-21A8,KS2A,-,-,-	
RA01	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
RA02	2001-000028	R-CARBON(S);1000HM,5%,1/2W,AA,TP,2.4X6.4	
CA04	2202-000720	C-CERAMIC,MLC-AXIAL;8.2nF,20%,16V,Y5R,TP	
CA05	2202-000720	C-CERAMIC,MLC-AXIAL;8.2nF,20%,16V,Y5R,TP	
CA06	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
CA07	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
LA04	2701-000180	INDUCTOR-AXIAL;33uH,5%,2.5x3.4mm	
LA05	2701-000180	INDUCTOR-AXIAL;33uH,5%,2.5x3.4mm	
JE01	3722-000143	JACK-PHONE;1P(VER),3.4mm,AG,BLK,NO	
JR01	3722-001031	JACK-RCA;3P,3.6MM,#18,AU	
CN06A	AA39-00070A	LEAD CONNECTOR-ASSY;-,-,-,-,-,-,-,-,-,YB	
CN01A	AA39-20068E	LEAD CONNECTOR-ASSY;-,YBNH025-08,67096-0	
PCB	AA41-10358B	PCB-A/V FRONT;SCT12A,1,FR-1,245x245x1.6T	
CA02	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
CA03	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
CN05A	AA39-20069D	LEAD CONNECTOR-ASSY;-,YBNH025-05,67096-0	

ASSY-POWER,CORD

	* AA96-20109C	ASSY-POWER,CORD;-,CP2/NO(4.0),H/C300,KKP	
	AA39-10006X	POWER-CORD;-,KKP419C,KLCE-2F,2.286MT,3P,	
	AA61-20284A	HOLDER;-,P-CORD,PP,VO,BLK,KE-002	

ASSY HOLDER SPK

	* AA91-00427A	ASSY HOLDER SPK;-,PP,8ohm/10W,BLK,SEMI-D	

REMOCON

	* AA59-00104B	REMOCON;-,TM59,SIM806E,29,L/GRAY,-,PAL	